

[Features](#) [Specs](#) [Accessories](#) [Applications](#) [Manuals](#) [How to Videos](#) [Reviews](#) [Where to Buy](#)

Excellent source of power for RVs, including 13,500 BTU AC units, and basic home backup power

This popular model can operate a wide variety of appliances, including a furnace, fridge, microwave, most 13,500 BTU RV AC units, and much more. Take a look at the applications tab for more examples.




Super quiet - less noise than normal conversation

So quiet, your neighbors will thank you. The EU3000iS operates at 50 to 57 dB(A), which is less noise than a normal conversation. This makes it ideal for camping, RV power and any other activity that requires quiet operation.

[Learn More](#)

Convenient electric starting


Easy recoil starting is also available as a back up.



Fuel efficient - Runs up to 20 hours on 3.4 gal of fuel

Thanks to our exclusive Eco Throttle System, the EU3000iS offers great fuel efficiency. Runs from 7.2 to 20 hours on a single tank, depending on the load. This makes it great for overnight power.

[Learn More](#)



Advanced inverter technology - reliable power for computers and other sensitive equipment

Honda's inverter technology means stable, clean power in a smaller, lighter package. The precision of Honda's inverter technology ensures our inverter generators produce power that is as reliable as the power you get from your outlets at home.

[Learn More](#)



[Back to Top](#)

Add more power with parallel capability

Need more power? Add a second EU3000iS for additional power. Two identical models can be paralleled with an optional cable.

[Features](#) [Specs](#) [Accessories](#) [Applications](#) [Manuals](#) [How to Videos](#) [Reviews](#) [Where to Buy](#)



12V - 12.0A DC output

The EU3000iS has a DC outlet for use when charging 12-volt automotive type batteries. (Requires an optional charging cord.)



3 year residential and commercial warranty

You can rest easy, knowing your generator is covered from top to bottom for 3 full years.

Protected by Oil Alert?

Protects the generator by shutting the engine off when low oil is detected.

USDA-qualified spark arrestor/muffler

Circuit protected

Protects the generator from being overloaded.

Specifications

Engine

Honda GX200

Displacement

196cc

AC Output

120V 3000W max.(25A) 2800W rated (23.3A)

[Back to Top](#)

Receptacles

20A 125V Duplex, 30A 125V Locking Plug

[Features](#) [Specs](#) [Accessories](#) [Applications](#) [Manuals](#) [How to Videos](#) [Reviews](#) [Where to Buy](#)

DC Output

12V, 144W (12A)

Starting System

Recoil, electric

Fuel Tank Capacity

3.4 gal.

Run Time per Tankful

7.1 hrs. @ rated load, 20 hrs. @ 1/4 load

Dimensions (L x W x H)

25.9" x 17.6" x 22.0"

Noise Level

57 dB(A) @ rated load, 50 dB(A) @ 1/4 load

Dry Weight

131 lbs.

Residential Warranty

3 Years

Commercial Warranty

3 Years

[WARNING: California Prop 65 Information](#)

Accessories



Storage Cover



2 or 4 Wheel Kit

[Back to Top](#)

